

## LCD Cable Testers



### Function comparison of LCD Cable Testers

Function	NF-308	NF-388	NF-300	NF-8200	NF-8208
Tracing Cables	RJ45+RJ11 +BNC+USB	RJ45+RJ11 +BNC+USB	RJ45+RJ11 +BNC+USB	RJ45+RJ11	RJ45
Measure cable length	RJ45	RJ45	RJ45+BNC	RJ45+RJ11	RJ45
Check cable errors	RJ45+BNC	RJ45+BNC	RJ45+BNC+RJ11	RJ45+RJ11	RJ45
Polarity testing	✓	✓	×	×	×
Port flash	✓	✓	✓	×	×
Anti-current interference	OK	OK	Good	Good	OK
Power supply	9V Battery	9V Battery	9V Battery	1.5V AA	1.5V AA
Storage for calibration data	3 Sets	3 Sets	4 Sets	4 Sets	3 Sets
Remote units	1PCS	8PCS	1PCS	1PCS	1PCS

## WIRE FAULT LOCATOR

### NF-308



#### Applications Include:

1. Hunt RJ11/RJ45/BNC/USB cable and check wire map for RJ45 & BNC cable.
2. Measure UTP/STP cable length for 1000m.
3. Polarity test extra function and DC voltage measurement.
4. Trace cables under connect the switches/router.
5. Hub blink for locating network port by the flashing port light on Hub/switch.

#### Benefits:

1. Light weight, easy to handle.
2. Verifies RJ45 and BNC conductors.
3. Enables cables to be located even when totally concealed.
4. 8 Remote identifiers are included (NF-388)

#### Attention:

1. Don't connect high voltage lines to avoid burning out the machine.
2. Don't insert telephone cable into RJ45 Port.
3. Put into the right place to avoid hurting others, because of the sharp part.
4. Read the user manual before use it.

#### Standard carton:

Carton size: 48.8 × 43.5 × 44.5cm  
Quantity: 30PCS/CTN  
Weight: 22.2KG

#### Technical indexes:

##### NF-308/NF-388 Transmitter specifications

Indicator	LCD 53x25mm, with back light
Tone frequency	455KHz
Max. distance of transmission	2km
Max. distance of cable map	1000m
Max. working current	≤70mA
Tone mode	2 Tone adjustable
Compatible connectors	3xRJ45(MAIN, Scan, Port flash) RJ11, BNC, USB
Max. signal voltage	15Vp-p
Function selection	3 position buttons & 1 power switch
Function and faults LCD display	LCD display(Wiremap, Tone, Short, No adapter, UTP/STP, Low battery)
Cable map indication	LCD(Pin#1-Pin#8)
Shielded indication	LCD(G for shielded)
Voltage protection	AC 60V/DC 42V
Low battery display	LCD (6.5V)
Battery type	DC 9.0V(NEDA 1604/6F22 DC9Vx1pcs)
Dimension (LxWxH)	185x80x32mm

##### NF-308 Receiver specifications

Frequency	455KHz
The Max. working current	≤70mA
Ear jack	1
LED illumination	2 LEDs
Battery type	DC 9.0V(NEDA 1604/6F22 DC9Vx1pcs)

##### NF-308 Remote unit specifications

Compatible connectors	RJ45, BNC
Dimension (LxWxH)	107x30x24mm

### NF-388

