

# Voltage Detector & Phone Checker



## NON-CONTACT AC VOLTAGE DETECTOR

### NF-608



#### Description:

The NF-608 is useful for identifying hot and neutral conductors, finding a break in a wire, and detecting the presence of AC voltage at outlets, switches, circuit breakers, fuses and cables.

#### Key features:

- Identifying hot and neutral conductors.
- Safe, non-contact design.
- Locate wire break point.
- Detect 50-1000V AC voltage.
- Bright LED and sound alert if voltage detected.
- Detect live wire.

#### Standard carton:

Carton size: 43 × 37 × 37cm  
Quantity: 200PCS/CTN  
Weight: 17KG

#### Standard Configuration:

Main body  
2 AAA battery  
1 User manual  
1 Blister  
1 card

#### Technical parameters :

Model	NF-608
Color	Grey /Red/Blue
Name	Non-contact AC Voltage Detector
Safe	Non-contact design
Indicators	Led and tone
Voltage range	50VAC to 1000VAC
Frequency range	50 HZ to 500HZ
Measurement category	Category 1v, 1000v per ul 61010
Operating conditions	Temperature: 0 to 40°C Less than 80% relative humidity Altitude: 2000m maximum (Indoor use only)

